



MECHATRONIC COMPANY

TRANSFORMATOREN DROSSELN NETZGERÄTE

Absicherungstabelle Einphasentrafos, Industrie

| Typ | Leistung [VA] | Leistungsschalter | 550 [V] | 525 [V] | 500 [V] | 480 [V] | 460 [V] | 440 [V] | 415 [V] | 400 [V] | 380 [V] | 240 [V] | 230 [V] | 220 [V] | 208 [V] | 200 [V] | |
|----------|------------------|-------------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|---|
| ETI00.20 | 200 | | 0,40 A | 0,42 A | 0,44 A | 0,46 A | 0,48 A | 0,50 A | 0,53 A | 0,55 A | 0,58 A | 0,92 A | 0,96 A | 1,00 A | 1,06 A | 1,10 A | |
| | | 3RV1421-0FA10 | x | x | x | x | x | x | | | | | | | | | |
| | | 3RV1421-0GA10 | | | | x | x | x | x | x | x | | | | | | |
| | | 3RV1421-0KA10 | | | | | | | | | | | x | x | x | x | x |
| ETI00.25 | 250 | | 0,50 A | 0,52 A | 0,55 A | 0,57 A | 0,60 A | 0,63 A | 0,66 A | 0,69 A | 0,72 A | 1,15 A | 1,20 A | 1,25 A | 1,32 A | 1,38 A | |
| | | 3RV1421-0GA10 | x | x | x | x | x | x | | | | | | | | | |
| | | 3RV1421-0HA10 | | | | x | x | x | x | x | x | | | | | | |
| | | 3RV1421-1AA10 | | | | | | | | | | | x | x | x | x | x |
| ETI00.32 | 320 | | 0,64 A | 0,67 A | 0,70 A | 0,73 A | 0,77 A | 0,80 A | 0,85 A | 0,88 A | 0,93 A | 1,47 A | 1,53 A | 1,60 A | 1,69 A | 1,76 A | |
| | | 3RV1421-0HA10 | x | x | x | x | x | x | | | | | | | | | |
| | | 3RV1421-0JA10 | | | | x | x | x | x | x | x | | | | | | |
| | | 3RV1421-1BA10 | | | | | | | | | | | x | x | x | x | x |
| ETI00.40 | 400 | | 0,80 A | 0,84 A | 0,88 A | 0,92 A | 0,96 A | 1,00 A | 1,06 A | 1,10 A | 1,16 A | 1,83 A | 1,91 A | 2,00 A | 2,12 A | 2,20 A | |
| | | 3RV1421-0JA10 | x | x | x | x | x | x | | | | | | | | | |
| | | 3RV1421-0KA10 | | | | x | x | x | x | x | x | | | | | | |
| | | 3RV1421-1CA10 | | | | | | | | | | | x | x | x | x | x |
| ETI00.50 | 500 | | 1,00 A | 1,05 A | 1,10 A | 1,15 A | 1,20 A | 1,25 A | 1,33 A | 1,38 A | 1,45 A | 2,29 A | 2,39 A | 2,50 A | 2,64 A | 2,75 A | |
| | | 3RV1421-0KA10 | x | x | x | x | x | x | | | | | | | | | |
| | | 3RV1421-1AA10 | | | | x | x | x | x | x | x | | | | | | |
| | | 3RV1421-1DA10 | | | | | | | | | | | x | x | x | x | x |
| ETI00.63 | 630 | | 1,26 A | 1,32 A | 1,39 A | 1,44 A | 1,51 A | 1,58 A | 1,67 A | 1,73 A | 1,82 A | 2,89 A | 3,01 A | 3,15 A | 3,33 A | 3,47 A | |
| | | 3RV1421-1AA10 | x | x | x | x | x | x | | | | | | | | | |
| | | 3RV1421-1BA10 | | | | x | x | x | x | x | x | | | | | | |
| | | 3RV1421-1EA10 | | | | | | | | | | | x | x | x | x | x |
| ETI00.80 | 800 | | 1,60 A | 1,68 A | 1,76 A | 1,83 A | 1,91 A | 2,00 A | 2,12 A | 2,20 A | 2,32 A | 3,67 A | 3,83 A | 4,00 A | 4,23 A | 4,40 A | |
| | | 3RV1421-1BA10 | x | x | x | x | x | x | | | | | | | | | |
| | | 3RV1421-1CA10 | | | | x | x | x | x | x | x | | | | | | |
| | | 3RV1421-1FA10 | | | | | | | | | | | x | x | x | x | x |
| ETI01.00 | 1000 | | 2,00 A | 2,10 A | 2,20 A | 2,29 A | 2,39 A | 2,50 A | 2,65 A | 2,75 A | 2,89 A | 4,58 A | 4,78 A | 5,00 A | 5,29 A | 5,50 A | |
| | | 3RV1421-1CA10 | x | x | x | x | x | x | | | | | | | | | |
| | | 3RV1421-1DA10 | | | | x | x | x | x | x | x | | | | | | |
| | | 3RV1421-1GA10 | | | | | | | | | | | x | x | x | x | x |
| ETI01.30 | 1300 | | 2,60 A | 2,72 A | 2,86 A | 2,98 A | 3,11 A | 3,25 A | 3,45 A | 3,58 A | 3,76 A | 5,96 A | 6,22 A | 6,50 A | 6,88 A | 7,15 A | |
| | | 3RV1421-1DA10 | x | x | x | x | x | x | | | | | | | | | |
| | | 3RV1421-1EA10 | | | | x | x | x | x | x | x | | | | | | |
| | | 3RV1421-1HA10 | | | | | | | | | | | x | x | x | x | x |
| ETI01.60 | 1600 | | 3,20 A | 3,35 A | 3,52 A | 3,67 A | 3,83 A | 4,00 A | 4,24 A | 4,40 A | 4,63 A | 7,33 A | 7,65 A | 8,00 A | 8,46 A | 8,80 A | |
| | | 3RV1421-1EA10 | x | x | x | x | x | x | | | | | | | | | |
| | | 3RV1421-1FA10 | | | | x | x | x | x | x | x | | | | | | |
| | | 3RV1421-1JA10 | | | | | | | | | | | x | x | x | x | x |

Irrtum und Änderungen vorbehalten. Es gelten die Liefer- und Zahlungsbedingungen (AGB) der Mechatronic Company Elektrotechnik GesmbH.



MECHATRONIC COMPANY

TRANSFORMATOREN DROSSELN NETZGERÄTE

| Typ | Leistung [VA] | Leistungsschalter | 550 [V] | 525 [V] | 500 [V] | 480 [V] | 460 [V] | 440 [V] | 415 [V] | 400 [V] | 380 [V] | 240 [V] | 230 [V] | 220 [V] | 208 [V] | 200 [V] |
|----------|------------------|-------------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|
| ETI02.00 | 2000 | | 4,00 A | 4,19 A | 4,40 A | 4,58 A | 4,78 A | 5,00 A | 5,30 A | 5,50 A | 5,79 A | 9,17 A | 9,57 A | 10,00 A | 10,58 A | 11,00 A |
| | | 3RV1421-1FA10 | x | x | x | x | x | x | | | | | | | | |
| | | 3RV1421-1GA10 | | | | x | x | x | x | x | x | | | | | |
| | | 3RV1421-1KA10 | | | | | | | | | | x | x | x | x | x |
| ETI02.50 | 2500 | | 5,00 A | 5,24 A | 5,50 A | 5,73 A | 5,98 A | 6,25 A | 6,63 A | 6,88 A | 7,24 A | 11,46 A | 11,96 A | 12,50 A | 13,22 A | 13,75 A |
| | | 3RV1421-1GA10 | x | x | x | x | x | x | | | | | | | | |
| | | 3RV1421-1HA10 | | | | | | | x | x | x | | | | | |
| | | 3RV1421-4AA10 | | | | | | | | | | x | x | x | x | x |
| ETI03.20 | 3200 | | 6,40 A | 6,70 A | 7,04 A | 7,33 A | 7,65 A | 8,00 A | 8,48 A | 8,80 A | 9,26 A | 14,67 A | 15,30 A | 16,00 A | 16,92 A | 17,60 A |
| | | 3RV1421-1HA10 | x | x | x | x | x | x | | | | | | | | |
| | | 3RV1421-1JA10 | | | | x | x | x | x | x | x | | | | | |
| | | 3RV1421-4BA10 | | | | | | | | | | x | x | x | x | x |
| ETI04.00 | 4000 | | 8,00 A | 8,38 A | 8,80 A | 9,17 A | 9,57 A | 10,00 A | 10,60 A | 11,00 A | 11,58 A | 18,33 A | 19,13 A | 20,00 A | 21,15 A | 22,00 A |
| | | 3RV1421-1JA10 | x | x | x | x | x | x | | | | | | | | |
| | | 3RV1421-4KA10 | | | | x | x | x | x | x | x | | | | | |
| | | 3RV1431-4DA10 | | | | | | | | | | x | x | x | x | x |
| ETI05.00 | 5000 | | 10,00 A | 10,48 A | 11,00 A | 11,46 A | 11,96 A | 12,50 A | 13,25 A | 13,75 A | 14,47 A | 22,92 A | 23,91 A | 25,00 A | 26,44 A | 27,50 A |
| | | 3RV1421-1KA10 | x | x | x | x | x | x | | | | | | | | |
| | | 3RV1421-4AA10 | | | | x | x | x | x | x | x | | | | | |
| | | 3RV1431-4EA10 | | | | | | | | | | x | x | x | x | x |
| ETI06.30 | 6300 | | 12,60 A | 13,20 A | 13,86 A | 14,44 A | 15,07 A | 15,75 A | 16,70 A | 17,33 A | 18,24 A | 28,88 A | 30,13 A | 31,50 A | 33,32 A | 34,65 A |
| | | 3RV1421-4AA10 | x | x | x | x | x | x | | | | | | | | |
| | | 3RV1431-4BA10 | | | | | | | x | x | x | | | | | |
| | | 3RV1431-4FA10 | | | | | | | | | | x | x | x | x | x |
| ETI08.00 | 8000 | | 16,00 A | 16,76 A | 17,60 A | 18,33 A | 19,13 A | 20,00 A | 21,20 A | 22,00 A | 23,16 A | 36,67 A | 38,26 A | 40,00 A | 42,31 A | 44,00 A |
| | | 3RV1431-4BA10 | x | x | x | x | x | x | | | | | | | | |
| | | 3RV1431-4DA10 | | | | x | x | x | x | x | x | | | | | |
| | | 3RV1431-4FA10 | | | | | | | | | | x | x | x | | |
| | | auf Anfrage | | | | | | | | | | | | | | |
| ETI10.00 | 10000 | | 20 A | 21 A | 22 A | 23 A | 24 A | 25 A | 27 A | 28 A | 29 A | 46 A | 48 A | 50 A | 53 A | 55 A |
| | | 3RV1431-4DA10 | x | x | x | x | x | x | | | | | | | | |
| | | 3RV1431-4EA10 | | | | x | x | x | x | x | x | | | | | |
| | | auf Anfrage | | | | | | | | | | | | | | |
| ETI13.00 | 13000 | | 26 A | 27 A | 29 A | 30 A | 31 A | 33 A | 34 A | 36 A | 38 A | 60 A | 62 A | 65 A | 69 A | 72 A |
| | | 3RV1431-4EA10 | x | x | x | x | x | | | | | | | | | |
| | | 3RV1431-4FA10 | | | x | x | x | x | x | x | x | | | | | |
| | | auf Anfrage | | | | | | | | | | | | | | |
| ETI16.00 | 16000 | | 32 A | 34 A | 35 A | 37 A | 38 A | 40 A | 42 A | 44 A | 46 A | 73 A | 77 A | 80 A | 85 A | 88 A |
| | | 3RV1431-4FA10 | x | x | x | x | x | x | | | | | | | | |
| | | auf Anfrage | | | | | | | | | | | | | | |
| ETI20.00 | 20000 | | 40 A | 42 A | 44 A | 46 A | 48 A | 50 A | 53 A | 55 A | 58 A | 92 A | 96 A | 100 A | 106 A | 110 A |
| | | auf Anfrage | | | | | | | | | | | | | | |
| ETI25.00 | 25000 | | 50 A | 52 A | 55 A | 57 A | 60 A | 63 A | 66 A | 69 A | 72 A | 115 A | 120 A | 125 A | 132 A | 138 A |
| | | auf Anfrage | | | | | | | | | | | | | | |

Irrtum und Änderungen vorbehalten. Es gelten die Liefer- und Zahlungsbedingungen (AGB) der Mechatronic Company Elektrotechnik GesmbH.



MECHATRONIC COMPANY

TRANSFORMATOREN DROSSELN NETZGERÄTE

| Typ | Leistung [VA] | Leistungsschalter | 550 [V] | 525 [V] | 500 [V] | 480 [V] | 460 [V] | 440 [V] | 415 [V] | 400 [V] | 380 [V] | 240 [V] | 230 [V] | 220 [V] | 208 [V] | 200 [V] |
|-----------|------------------|-------------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|------------|
| ETI32.00 | 32000 | | 64 A | 67 A | 70 A | 73 A | 77 A | 80 A | 85 A | 88 A | 93 A | 147 A | 153 A | 160 A | 169 A | 176 A |
| | | auf Anfrage | | | | | | | | | | | | | | |
| ETI40.00 | 40000 | | 80 A | 84 A | 88 A | 92 A | 96 A | 100 A | 106 A | 110 A | 116 A | 183 A | 191 A | 200 A | 212 A | 220 A |
| | | auf Anfrage | | | | | | | | | | | | | | |
| ETI50.00 | 50000 | | 100 A | 105 A | 110 A | 115 A | 120 A | 125 A | 133 A | 138 A | 145 A | 229 A | 239 A | 250 A | 264 A | 275 A |
| | | auf Anfrage | | | | | | | | | | | | | | |
| ETI63.00 | 63000 | | 126 A | 132 A | 139 A | 144 A | 151 A | 158 A | 167 A | 173 A | 182 A | 289 A | 301 A | 315 A | 333 A | 347 A |
| | | auf Anfrage | | | | | | | | | | | | | | |
| ETI80.00 | 80000 | | 160 A | 168 A | 176 A | 183 A | 191 A | 200 A | 212 A | 220 A | 232 A | 367 A | 383 A | 400 A | 423 A | 440 A |
| | | auf Anfrage | | | | | | | | | | | | | | |
| ETI100.00 | 100000 | | 200 A | 210 A | 220 A | 229 A | 239 A | 250 A | 265 A | 275 A | 289 A | 458 A | 478 A | 500 A | 529 A | 550 A |
| | | auf Anfrage | | | | | | | | | | | | | | |

Irrtum und Änderungen vorbehalten. Es gelten die Liefer- und Zahlungsbedingungen (AGB) der Mechatronic Company Elektrotechnik GesmbH.